

DUAL OUTPUT 30-0-30 V DC /1 Amps



Product Categories: [DC Regulated Power Supply Single/Dual Channel](#), [DC Regulated Power Supply Single/Dual Channel](#), [Electronics](#), [Engineering Equipment](#)

Product Page:

<https://www.labappara.com/product/dual-output-30-0-30-v-dc-1-amps/>

Product Description

DUAL OUTPUT 30-0-30 V DC /1 Amps

Dual Output DC Regulated Power Supply are constant Voltage & Constant Current type supplies , have high regulation for Load & Line Voltage variation . The supply can be use in independent & tracking mode . The supply are protected against short circuit & over load . The output current can be controlled to any value from 0 to maximum

INPUT VOLTAGE	:	230V \pm 10% AC 50 Hz
LOAD REGULATION CV	:	\pm 0.05 % \pm 3mV From no load to full load
LOAD REGULATION CC	:	0.05% 1mA From no load to full load
LINE REGULATION CV	:	\pm 0.01 % \pm 3mV for 10% variation input voltage
LINE REGULATION CC	:	0.01% 1mA for 10% variation input voltage
OPERATING MODE	:	Independent & Tracking mode
RIPPLE	:	Less than 1 mV
METER	:	Four Digital meters to monitor the output

voltage & current

voltage & current of

A & B Supply

ACCURACY : 1% + 1 Digit +

PROTECTION : Against short circuit & over load